**QUEEN'S
UNIVERSITY
BELFAST**

Sparse multi-carrier index keying OFDM with index separation over correlated sub-carriers

Ko, Y., & Choi, J. (2015). Sparse multi-carrier index keying OFDM with index separation over correlated sub-carriers. In *2015 International Conference on Information and Communication Technology Convergence (ICTC)* (pp. 307-312). Institute of Electrical and Electronics Engineers Inc.. <https://doi.org/10.1109/ICTC.2015.7354553>

Published in:

2015 International Conference on Information and Communication Technology Convergence (ICTC)

Document Version:

Peer reviewed version

Queen's University Belfast - Research Portal:

[Link to publication record in Queen's University Belfast Research Portal](#)

Publisher rights

Copyright 2015 IEEE.

Personal use of this material is permitted. Permission from IEEE must be obtained for all other uses, in any current or future media, including reprinting/republishing this material for advertising or promotional purposes, creating new collective works, for resale or redistribution to servers or lists, or reuse of any copyrighted component of this work in other works.

General rights

Copyright for the publications made accessible via the Queen's University Belfast Research Portal is retained by the author(s) and / or other copyright owners and it is a condition of accessing these publications that users recognise and abide by the legal requirements associated with these rights.

Take down policy

The Research Portal is Queen's institutional repository that provides access to Queen's research output. Every effort has been made to ensure that content in the Research Portal does not infringe any person's rights, or applicable UK laws. If you discover content in the Research Portal that you believe breaches copyright or violates any law, please contact openaccess@qub.ac.uk.

Sparse Multi-Carrier Index Keying OFDM with Index Separation over Correlated Sub-Carriers

Youngwook Ko

School of Electronics, Electri. Eng. and Computer Science
Queen's University of Belfast
Belfast, BT3 9DT, United Kingdom
Email: y.ko@qub.ac.uk

Jinho Choi

School of Information and Communications
Gwangju Institute of Science and Technology
Gwangju, 500-712, South Korea
Email: jchoi0114@gist.ac.kr

Abstract—In this paper, we propose a sparse multi-carrier index keying (MCIK) method for orthogonal frequency division multiplexing (OFDM) system, which uses the indices of sparse sub-carriers to transmit the data, and improve the performance of signal detection in highly correlated sub-carriers. Although a receiver is able to exploit a power gain with precoding in OFDM, the sensitivity of the signal detection is usually high as the orthogonality is not retained in highly dispersive environments. To overcome this, we focus on developing the trade-off between the sparsity of the MCIK, correlation, and performances, analyzing the average probability of the error propagation imposed by incorrect index detection over highly correlated sub-carriers. In asymptotic cases, we are able to see how sparsity of MCIK should be designed in order to perform superior to the classical OFDM system. Based on this feature, sparse MCIK based OFDM is a better choice for low detection errors in highly correlated sub-carriers.

Index Terms—Sparse multi-carrier index keying, non-orthogonal OFDM, detection error propagation.

I. INTRODUCTION

Orthogonal frequency division multiplexing (OFDM) has been adopted in the majority of today and future communication standards such as IEEE 802.11, 3GPP's LTE-Advanced, due to its robustness to multipath fading. The performance of these systems with increased bandwidth is heavily dependent on an increased sensitivity to non-orthogonality of sub-carriers due to frequency offset and Doppler shift [1] as well as transmission nonlinearity caused by the non-constant power ratio of OFDM symbols [2], [3].

In [4], [5], the so-called sub-carrier-index modulation (SIM) OFDM scheme has been proposed to outperform the classical OFDM systems. The sub-carrier index becomes additional resource to decrease the bit error rate (BER) faster than the classical OFDM with only a few sub-carrier activation. Recently, the effects of channel estimation errors on the approximate pairwise error probability (PEP) of the OFDM modulating the index of sub-carrier was discussed in [6]. OFDM modulating the indices of active sub-carriers are more recently combined with space-time block coding [7] and with compressive sensing [8], for better performance. They are evaluated based on orthogonal sub-carriers. In practice, however, orthogonality of sub-carriers at the receiver is hard to retain, especially in frequency dispersive channels. For the robustness to the non-orthogonality of sub-carriers, precoding

can be used in SIM OFDM. In this case, the detection error probability can still be high as the orthogonality is not retained.

In this work, we propose SIM for precoded OFDM with a small number of activated sub-carriers which are designed to be apart over correlated sub-carriers. Since only a fraction of sub-carriers are activated, the resulting modulation is referred to as sparse multi-carrier index keying (MCIK). The contribution of this paper is three-fold. We first analyze the propagation error rate (PER) expression of sparse MCIK for any number of active sub-carriers and secondly investigate the effect of propagation of error imposed by the nature of sparse MCIK in highly correlated sub-carriers. In [4], [5], the BER is limited by a fixed number of active, orthogonal sub-carriers that differs from what we consider herein. For example, the approach in [5] cannot be used directly with either the small or large active sub-carriers as well as non-orthogonal sub-carriers. Our contribution is thirdly to develop the trade-off between the sparsity of the MCIK, correlation, and PER at various extreme cases. In the presence of highly correlated sub-carriers, it aims to provide theoretical guidelines with the fundamental question: how sparsity of the MCIK OFDM should be chosen along with the maximum index separation to decrease the detection error rate, outperforming the classical OFDM.

II. SYSTEM MODEL

We consider an OFDM transmission with L sub-carriers. Denote by $\mathbf{s}$ an OFDM signal block and its elements are referred to as data symbols, for convenience. The received signal in the frequency domain is given by

$$\mathbf{y} = \mathbf{H}\mathbf{s} + \mathbf{n},$$

where $\mathbf{H} = \text{diag}(H_1, \dots, H_L)$ is a diagonal channel matrix, H_i represent Rayleigh fading channel coefficients observed in subcarrier i , being complex Gaussian with zero mean and unit variance, i.e., $H_i \sim \mathcal{CN}(0, 1), \forall i$, and $\mathbf{n}$ is the independent, additive white Gaussian noise (AWGN) vector, i.e., $\mathbf{n} \sim \mathcal{CN}(\mathbf{0}, N_0\mathbf{I})$.

In practice, we face frequency dispersive channels, due to the presence of, e.g., phase noise and frequency offsets. That is, $H_i, \forall i$ are non-independent, and identically distributed leading to a heterogeneous cross correlation coefficient: $\rho_{i,j} =$

$\mathbb{E}(H_i H_j^*) \in [0, 1)$, where we have $\rho_{i,j} \neq \rho_{l,m}$ and $\rho_{i,j} = \rho_{j,i}, \forall i, j, l, m$.

In the classical OFDM system, each data symbol is an element of a given signal constellation. That is, $s_l \in \mathcal{S}$, where s_l is the l th element of $\mathbf{s}$ and $\mathcal{S}$ represents the signal constellation. Using the maximum likelihood (ML) detector, s_l can be detected from the l th element of $\mathbf{y}$, i.e., y_l , as

$$\hat{s}_l = \arg \min_{s_l \in \mathcal{S}} |y_l - H_l s_l|^2.$$

III. SPARSE MULTI-CARRIER INDEX KEYING OFDM WITH INDEX SEPARATION

Let L sub-carriers be composed of K clusters, each containing N sub-carriers (i.e., $L = KN$). Denote by $\mathbf{W}$ the precoding matrix and by $\mathbf{x}$ the K non-zero data symbols. The received signal can be

$$\begin{aligned} \mathbf{y} &= \mathbf{H}\mathbf{W}\mathbf{x} + \mathbf{n}, \\ &= \mathbf{H}\mathbf{s} + \mathbf{n}, \end{aligned} \quad (1)$$

where $\mathbf{s} = \mathbf{W}\mathbf{x}$ is the precoded OFDM signal block, $\mathbf{W} = [\mathbf{w}_1, \dots, \mathbf{w}_K]$, its k th column vector has $\|\mathbf{w}_k\|_0 = 1, \forall k$. For every transmission, $\mathbf{s}$ is used to modulate sub-carriers, as in the classical OFDM system, but it differs from that the modulated sub-carriers are only a fraction of sub-carriers. That is, at cluster k $\mathbf{w}_k$ decides part of sub-carriers to modulate. Unlike the conventional MCIK-OFDM [6], [9] whose sub-carrier indices are assumed to be adjacent to each other, we propose the indices of sub-carriers at cluster k are separated by α_Δ , i.e., $\{\alpha_k, \alpha_k + \alpha_\Delta, \dots, \alpha_k + (N-1)\alpha_\Delta\}$. Thus, α_Δ denotes the minimum separation distance between indices of sub-carriers at each cluster.

For MCIK OFDM with the index separation, most s_l 's are zero, while information can be conveyed by both non-zero data symbols (in $\mathbf{s}$) and indices of K active sub-carriers. Consider K non-zero data symbols in $\mathbf{s}$, i.e., $\mathbf{s}$ is a K -sparse signal vector, which leads to $\|\mathbf{s}\|_0 = K$. Given L , α_Δ is a design parameter as an integer, i.e., $\alpha_\Delta \in \{1, \dots, K\}$. In other words, the proposed scheme can benefit from properly designing both α_Δ and K , over non-orthogonal sub-carrier environments. We denote the average signal-to-noise ratio (SNR) by $\bar{\gamma} = \tau E_s / N_0$ where E_s denotes the average power for non-zero data symbol and τ represents the K -sparsity ratio, i.e., $\tau = L/K$.

Denote by m_I the number of information bits that are conveyed through the indices of K sub-carriers. This is given by

$$m_I = \lfloor \log_2 B(L, K) \rfloor,$$

where $B(\cdot)$ denotes the binomial coefficient. Denote by m_D the number of information bits that can be sent by the non-zero data symbols. That is $m_D = K \lfloor \log_2 |\mathcal{S}| \rfloor$ [9]. For example, when $L = 64$ and $K = 6$, we have $m_I = 26$ bits and each non-zero data symbol can represent $\log_2 |\mathcal{S}|$ bits. Thus, the total number of transmit bits is

$$R = \lfloor \log_2 B(L, K) \rfloor + K \log_2 |\mathcal{S}|, \quad (2)$$

when $|\mathcal{S}|$ is a power of 2 such as $|\mathcal{S}| = M$ for M-QAM.

IV. ERROR PROPAGATION ANALYSIS

We consider two step approach for detection. The ML detection can be considered to detect $\mathbf{s}$ in MCIK, and the indices of non-zero elements of the estimated $\mathbf{s}$ are used to detect m_I . Denote $\tilde{\mathcal{S}} = \mathcal{S} \cup \{0\}$, which is the extended signal constellation of $\mathcal{S}$ including zero. Based on this, the ML detection can be made as

$$\begin{aligned} \hat{\mathbf{s}} &= \arg \min_{\mathbf{s}} \|\mathbf{r} - \mathbf{H}\mathbf{s}\|^2 \\ \text{subject to } s_l &\in \tilde{\mathcal{S}} \text{ and } \mathbf{s} \in \Sigma_K, \end{aligned} \quad (3)$$

where Σ_K is a set of possible K -sparse signals, which is defined as

$$\Sigma_K = \{ \mathbf{s} \mid \|\mathbf{s}\|_0 = K \} \quad (4)$$

and its cardinality is $|\Sigma_K| = 2^{m_I}$.

The symbol errors in MCIK result from three error cases [9]:

- (i) an incorrect index of active sub-carrier and an incorrect data symbol;
- (ii) an incorrect index of active sub-carrier and a correct data symbol; and
- (iii) a correct index of active sub-carrier and an incorrect data symbol.

Notice from these error cases that all symbol errors are relying on the accuracy of index detection, which acts an important role in the overall symbol error rate. This observation leads to that inaccuracy of index detection will cause propagation of errors on the detection of non-zero data symbols (for m_D) as well as index modulation symbols (for m_I). This error propagation is critical to analyze in the MCIK system.

A. Average PEP over non-orthogonal sub-carriers

Denote by $(s_{k,\alpha} \rightarrow s_{k,\tilde{\alpha}})$ the pairwise error event (PEE) that in cluster k active index α is incorrectly detected as $\tilde{\alpha}$ for $\alpha, \tilde{\alpha} \in \{1, \dots, L\}$ and $\alpha \neq \tilde{\alpha}$, given that α is transmitted within cluster k . Here, let $\alpha_\Delta = \min |\alpha - \tilde{\alpha}|$ and $\mathbf{s}_{k,\alpha} = \mathbf{w}_k x_k$ represent $\mathbf{s}$ of cluster k with all zero elements except the α th element.

Based on the PEE, the symbol error rate ($P_{s,k}$) can be imposed by incorrect index and is obtained, using the union bound, as [9]

$$P_{s,k} \leq \sum_{\alpha} \sum_{\tilde{\alpha} \neq \alpha} P(s_{k,\alpha} \rightarrow s_{k,\tilde{\alpha}}) \frac{1}{N}, \quad (5)$$

where $P(s_{k,\alpha} \rightarrow s_{k,\tilde{\alpha}})$ is the conditional pairwise error probability (PEP) of deciding $s_{k,\tilde{\alpha}}$ given that $s_{k,\alpha}$ and H_α are used, and the priori probabilities of $s_{k,\alpha}$ are equally likely.

Using the likelihood ratio test (LRT) in [10], the well-known PEP expression in (5) can be

$$P(s_{k,\alpha} \rightarrow s_{k,\tilde{\alpha}}) = Q \left(\sqrt{\frac{d_k}{4N_0}} \right), \quad (6)$$

where $Q(z) \triangleq \pi^{-1} \int_0^{\pi/2} e^{-z^2/2 \sin^2 \theta} d\theta$ is the error function and $d_k = \tau E_s (|H_\alpha|^2 + |H_{\tilde{\alpha}}|^2)$.

Consider the average PEP with the presence of positive correlation of sub-carriers. Denote by $z_\alpha |H_\alpha|^2$ and by $\tilde{z}_\alpha |H_{\tilde{\alpha}}|^2$, for simple notations. Then, (6) relies on both z_α and $\tilde{z}_\alpha$. The average PEP can be therefore obtained, using a joint probability distribution function (pdf) of z_α and $\tilde{z}_\alpha$, as

$$\int_0^\infty \int_0^\infty e^{-\frac{\tau E_s}{8N_0}(z_\alpha + \tilde{z}_\alpha)} p(\tilde{z}_\alpha | z_\alpha) p(z_\alpha) d\tilde{z}_\alpha dz_\alpha, \quad (7)$$

where $p(\cdot|\cdot)$ and $p(\cdot)$ represent the conditional pdf of $\tilde{z}_\alpha$ on z_α and the pdf of z_α , respectively.

Particularly with the proposed system model, we have $p(z_\alpha) = e^{-z_\alpha}$ and

$$p_{\tilde{z}_\alpha | z_\alpha}(\tilde{z} | z) = \frac{1}{\sigma_\epsilon^2} e^{-\frac{\tilde{z} + \rho_{\tilde{\alpha}, \alpha}^2}{\sigma_\epsilon^2}} I_0 \left(\sqrt{\tilde{z}z} \frac{|-2\rho_{\tilde{\alpha}, \alpha}|}{\sigma_\epsilon^2} \right), \quad (8)$$

where $\sigma_\epsilon^2 = (1 - \rho_{\tilde{\alpha}, \alpha}^2) \sigma_h^2$ with the normalized sub-carrier's variance $\sigma_h^2 = 1$ in our system model, $\rho_{\tilde{\alpha}, \alpha} \in [0, 1)$, $\forall \alpha, \tilde{\alpha}$, and $I_0(\cdot)$ stands for the modified bessel function of the first kind.

Using these pdfs and [11, (3.326.3)], we can compute the integrals in (7); for simplicity, detailed computation steps are omitted. Thus, the upper bound expression for the average PEP per cluster k can be in closed-form as

$$\begin{aligned} \text{aPEP}_k &\leq \frac{A(\bar{\gamma}, \sigma_\epsilon^2)^{-2}}{\pi} \left\{ \sigma_\epsilon^2 + \frac{A(\bar{\gamma}, \sigma_\epsilon^2)^{1/2}}{2} \right. \\ &\quad \times \left. \frac{|-2\rho_{\alpha, \tilde{\alpha}}| \Gamma(3/2)}{\sqrt{\sigma_\epsilon^2}} \left(1 + \frac{\bar{\gamma}}{8} + \frac{\rho_{\alpha, \tilde{\alpha}}^2}{\sigma_\epsilon^2} \right)^{-3/2} \right\}, \end{aligned} \quad (9)$$

where $A(\bar{\gamma}, \sigma_\epsilon^2) = 1 + \frac{\bar{\gamma}\sigma_\epsilon^2}{8}$. To further emphasize the impact of $\rho_{\alpha, \tilde{\alpha}}$, this inequality can be rewritten as

$$\begin{aligned} \text{aPEP}_k &\leq \frac{1}{\pi} \left(1 + \frac{(1 - \rho_{\alpha, \tilde{\alpha}}^2) \bar{\gamma}}{8} \right)^{-2} \left\{ (1 - \rho_{\alpha, \tilde{\alpha}}^2) \right. \\ &\quad \left. + \frac{|-\rho_{\alpha, \tilde{\alpha}}| \Gamma(3/2) (1 - \rho_{\alpha, \tilde{\alpha}}^2)}{1 + (1 - \rho_{\alpha, \tilde{\alpha}}^2) \bar{\gamma}/8} \right\}. \end{aligned} \quad (10)$$

B. Total average propagation error rate (APER)

From (5) and (10), the average probability of the error propagation imposed by the incorrect index detection can be obtained over the non-orthogonal sub-carriers and is given:

$$\begin{aligned} P_e(\bar{\gamma}, \Sigma_\rho) &\leq L^{-1} \sum_{k=1}^K \sum_{\alpha=1}^N \sum_{\tilde{\alpha} \neq \alpha}^N \text{aPEP}_k(\bar{\gamma}, \rho_{\alpha, \tilde{\alpha}}) \\ &= \tau^{-1} \sum_{\alpha=1}^N \sum_{\tilde{\alpha} \neq \alpha}^N \frac{1}{\pi} \left(1 + \frac{(1 - \rho_{\alpha, \tilde{\alpha}}^2) \bar{\gamma}}{8} \right)^{-2} \\ &\quad \times \left\{ (1 - \rho_{\alpha, \tilde{\alpha}}^2) + \frac{|-\rho_{\alpha, \tilde{\alpha}}| \Gamma(3/2) (1 - \rho_{\alpha, \tilde{\alpha}}^2)}{1 + (1 - \rho_{\alpha, \tilde{\alpha}}^2) \bar{\gamma}/8} \right\}, \end{aligned} \quad (11)$$

where Σ_ρ denotes a set of the cross correlation: $\Sigma_\rho = \{\rho_{\alpha, \tilde{\alpha}}\}$, $\forall \alpha, \tilde{\alpha}$, and recall that $\bar{\gamma} = \tau E_s / N_0$ and the sparsity ratio $\tau = L/K$. It can be observed from (11) that for given L , $P_e(\cdot, \cdot)$ relies on K as well as $\rho_{\alpha, \tilde{\alpha}}$'s.

To clearer view of such relationship between $\tau (= L/K)$ and $P_e(\cdot, \cdot)$, consider an example experiencing correlated sub-carriers with $\rho_{\alpha, \tilde{\alpha}} \leq \rho$, where $\rho = \max \rho_{\alpha, \tilde{\alpha}}$. $P_e(\cdot, \cdot)$ can be simplified to

$$\begin{aligned} P_e(\bar{\gamma}, \rho) &\leq \frac{L/K - 1}{\pi} \left(1 + \frac{(1 - \rho^2) \bar{\gamma}}{8} \right)^{-2} (1 - \rho^2) \\ &\quad \times \left\{ 1 + \frac{|-\rho| \Gamma(3/2)}{1 + (1 - \rho^2) \bar{\gamma}/8} \right\}. \end{aligned} \quad (12)$$

As can be seen in (12), $P_e(\cdot, \cdot)$ decreases with $\bar{\gamma}$ for given ρ . Here, due to the fact that $\bar{\gamma} = (L/K) E_s / N_0$, it is worth mentioning that for given ρ , $P_e(\cdot, \cdot)$ in (12) can still retain low, properly balancing L and K for the K -sparsity. Moreover, notice that ρ can decrease with the maximum separation of $\alpha_\Delta = K$, leading to decrease in $P_e(\cdot, \cdot)$.

V. ASYMPTOTIC RESULTS

We now consider four extreme cases to investigate asymptotic behaviors of the proposed scheme in terms of the average propagation error rate and explore the impacts of the K -sparsity and the correlated sub-carriers on it.

A. Case of high SNRs

For high SNRs, the average propagation error rates in (12) can be approximated as

$$\begin{aligned} P_e(\bar{\gamma}, \rho) &\approx c \frac{\tau - 1}{(1 - \rho^2)} \bar{\gamma}^{-2}, \\ &= \Theta((G(\tau, \rho) \text{SNR})^{-2}), \end{aligned} \quad (13)$$

where $\Theta(\cdot)$ is Big Theta notation, c denotes a scaling constant and $\text{SNR} = E_s / N_0$.

It is worth pointing out from (13) that the achievable diversity order is found to be two at high SNRs. Also, the power gain obtained is $G(\tau, \rho) = \tau \sqrt{(1 - \rho^2)/(\tau - 1)}$. This indicate that at high SNRs, a proper choice of $\tau (= L/K)$ can enhance the power gain for a given ρ . The power gain further increase, minimizing ρ with the choice of the maximum α_Δ for given L . Such flexibility is not available in the classical OFDM.

B. Case of large sparsity: $L/K \gg 1$

Let $K = \tau^{-1} L$ be an integer with a fixed $\tau^{-1} \ll 1$. As L grows, consider very large $\tau (= L/K)$ when $K \ll L$. In this asymptotic case, the power gain achieved in (13) can be approximated as

$$G(\tau, \rho) \approx \sqrt{\frac{(1 - \rho^2)L}{K}}.$$

We can asymptotically observe from this the trade-off between $G(\cdot, \cdot)$, τ , and ρ . That is, as L increases with the fixed but very large sparsity ratio τ , the power gain is proportional to τ and scales inversely with ρ .

Interestingly, this observation raises the fundamental question that, as L grows, how large K -sparsity is worthy to make $G(\cdot, \cdot)$ greater than or equal to the desired threshold (G_0), i.e.,

$G(\cdot, \cdot) \geq G_0$, with a positive ρ . We should properly find the sparsity ratio, satisfying

$$\tau \geq \frac{G_0^2}{1 - \rho^2}.$$

It asymptotically shows that *larger desired power gain, higher sparsity ratio τ needs*, at high ρ .

C. Case of highly correlated sub-carriers

When, in the ideal case, the orthogonality across sub-carriers is obtained having $\rho = 0$, then (12) can be simplified to

$$P_e(\bar{\gamma}) \leq \frac{\tau - 1}{\pi} \left(1 + \frac{\bar{\gamma}}{8}\right)^{-2}. \quad (14)$$

It can be seen that $P_e(\cdot)$ relies on $\tau = L/K$ and $\bar{\gamma} = \tau E_s/N_0$.

In practice, however, due to the presence of the hardware impairments (e.g., phase noise and frequency offsets), the non-orthogonality among the sub-carriers can be inevitable, providing $\rho > 0$. Accordingly, as ρ significantly grows in such frequency dispersive environments, (12) can be approximated, for a given τ , as

$$P_e(\bar{\gamma}, \rho) \approx \frac{\tau - 1}{\pi} (1 - \rho^2) (1 + |\rho| \Gamma(3/2)). \quad (15)$$

It is worth mentioning that at large ρ (i.e., $\rho \rightarrow 1$), *the average propagation error rates are not limited by the SNR, but only τ and ρ .*

In the MCIK with clusters, the level of ρ between *candidate* active sub-carriers (not between neighboring sub-carriers) can be effectively decreased by increasing α_Δ . In particular, consider the K clusters each comprising of N sub-carriers and we can select $\alpha_\Delta \in \{1, \dots, K\}$. The indices of sub-carriers at cluster k become $\{\alpha_k, \alpha_k + \alpha_\Delta, \alpha_k + 2\alpha_\Delta, \dots, \alpha_k + (N - 1)\alpha_\Delta\}$. The impact of α_Δ will be evaluated by simulations.

TABLE I
SIMULATED CORRELATION COEFFICIENTS

σ_{rms} (ns)	20 ns	50 ns	100 ns	200 ns
$\rho_{\alpha, \alpha+1}$	0.9995	0.9956	0.9817	0.927
$\rho_{\alpha, \alpha+\alpha_\Delta}$	0.9137	0.5878	0.3384	0.1761

VI. SIMULATION RESULTS

We simulate the MCIK OFDM with the index separation under the independent Rayleigh fading channel per sub-carrier with BPSK, and QPSK modulation. The IEEE 802.11b multipath channel model is used, and the channel gains H_l 's among sub-carriers are assumed to be non-orthogonal leading to the cross-correlations $\rho \in [0, 1)$. The simulated values for ρ when $L/K = 4$ are listed according to the rms delay spread in Table I. At the receiver, we employ the ML detection to estimate K -sparse signals.

Consider $L = 64$ sub-carriers with various sparsity ratios: $L/K \in \{4, \dots, 32\}$. In order to evaluate the proposed scheme, the average propagation of the error rates (PER) are obtained and the average symbol error rates are simulated in comparison with the classical OFDM and the MCIK OFDM

Fig. 1. The average propagation error rates of the MCIK-OFDM with the index separation are simulated with the maximum index separations, $\alpha_\Delta = 16$. In comparison, the general MCIK-OFDM without the index separation is depicted.

Fig. 2. The average propagation error rates are illustrated with the cross correlation. For the illustrations, we use that $L = 64$, $\tau = 4$ and $E_s/N_0 \in \{15, 20, 25\}$ (dB).

without the index separation. Since large propagation of the errors affects all the error cases in demodulation, we also evaluate how large sparsity of the MCIK signals would be effective to reduce the error propagation in the presence of non-orthogonal sub-carriers.

Fig. 1 depicts the simulated average PER of the MCIK OFDM with the index separation. For the illustrations, BPSK is employed for modulation of non-zero data symbols with $L = 64$, $\tau = 4$, and the maximum index separation $\alpha_\Delta = 16$. This figure illustrates the average PER decreases with

Fig. 3. The impact of the sparsity ratio on the average propagation error rates is illustrated at various cross correlations. We use when $L = 64$, $E_s/N_0 = 20$ dB, and $\rho \in \{0.8, 0.9, 0.95, 0.99\}$.

the diversity order of 2 at high SNRs. Compared to the MCIK-OFDM, this figure also illustrates that the average PER decreases faster when the index separation is maximized reducing the value for $\rho_{\alpha, \tilde{\alpha}}$. This validate our analysis in (13).

In Fig. 2, the average PER has been illustrated with the cross correlation ρ at several SNRs, i.e., $E_s/N_0 \in \{15, 20, 25\}$ (dB), for given $L = 64$, $\tau = 4$ and QPSK. From this figure, we can clearly observe the impact of ρ (relying on both the various index separation and the delay spread) on the average PER. Particularly, it can be seen in this figure that for given $E_s/N_0 = 25$ dB and $\tau = 4$, the average PER remains stationary at low and moderate ρ 's (e.g., $\rho \leq 0.5$) and grows significantly at large ρ 's (e.g., $\rho \geq 0.5$). This observation validates the analysis in (15).

Fig. 3 illustrates the average PER of the MCIK OFDM with the index separation with respect to the sparsity ratios at various ρ 's. For this, we use when $L = 64$, $\rho \in \{0.8, 0.9, 0.95, 0.99\}$ and $E_s/N_0 = 20$ dB. As observed from this figure, properly selecting the values of τ guarantees the average PER to be less than or equal to a target value, given ρ . For example, with the desired value of 10^{-3} , the average PER can remain less than or equal to 10^{-3} by selecting $\tau \geq 6$ when $\rho \leq 0.8$. Similarly, selecting τ at the minimum ($\tau \geq 8$) when $\rho \leq 0.9$ satisfies the average PER requirement. Under the average PER requirement, *higher correlation, larger sparsity needs*.

In Fig. 4, we simulate the average symbol error rates of the MCIK OFDM with the index separation. For this, the BPSK and QPSK modulations are used with $\tau = 2$ and $\tau = 4$, respectively. For comparison, the conventional OFDM and the MCIK OFDM with no index separation are also depicted. As observed, the MCIK OFDM with the index separation performs the best among them in a wide range of SNRs. For

Fig. 4. Compared with the OFDM and the MCIK OFDM, the average symbol error rates of the proposed scheme is depicted. For the proposed MCIK OFDM with index separation, we use when $L = 64$, BPSK, QPSK, and $\tau \in \{2, 4\}$.

example, for given value of 10^{-3} , the MCIK OFDM with the index separation and BPSK achieves the power gain of 5 dB over the OFDM scheme.

VII. CONCLUSION

We proposed the MCIK with index separation for precoded OFDM that can exploit a power gain with a low-complexity receiver structure in highly correlated sub-carriers. Since the MCIK requires only a small subset of active sub-carriers, the number of demodulators used can be small, which allows to build a receiver at a low cost. In addition, one important feature of the proposed scheme was to develop the trade-off between the sparsity ratio, SNR, cross correlation, and performances. Fundamentally, this new feature is important for designs of future MCIK OFDM systems, answering how large sparsity of the multi-carrier index keying with the index separation should be in correlated sub-carriers.

ACKNOWLEDGMENT

This work was supported by the Engineering and Physical Sciences Research Council [grant reference EP-M015521-1].

REFERENCES

- [1] T. Pollet, M. V. Bladel, and M. Moeneclaey, "BER sensitivity of OFDM systems to carrier frequency offset and wiener phase noise," *IEEE Trans. Commun.*, vol. 43, no. 2, pp. 191–193, Apr. 1995.
- [2] D. Goeckel and G. Ananthaswamy, "On the design of multidimensional signal sets for OFDM systems," *IEEE Trans. Commun.*, vol. 50, no. 3, pp. 442–452, Mar. 2002.
- [3] R. Baxley and G. Zhou, "Power saving analysis of peak-to-average power ratio reduction in OFDM," *IEEE Trans. Consumer Electronics*, vol. 50, no. 3, pp. 792–798, Aug. 2004.
- [4] R. Abu-alhiga and H. Haas, "Subcarrier-index modulation OFDM," in *Proc. IEEE Intl. Sym. Personal, Indoor, Mobile Radio Commun.*, Sep. 2009, pp. 177–181.

- [5] D. Tsonev, S. Sinanovic, and H. Haas, "Enhanced subcarrier index modulation (SIM) OFDM," in *Global Telecommunications Conference, IEEE*, Dec. 2011, pp. 728–732.
- [6] E. Basar, U. Aygolu, E. Panayirci, and H. V. Poor, "Orthogonal frequency division multiplexing with index modulation," *IEEE Trans. Signal Process.*, vol. 61, no. 22, pp. 5536–5549, Nov. 2013.
- [7] E. Basar, "OFDM with index modulation using coordinated interleaving," *IEEE Wireless Commun. Lett.*, vol. 99, Feb. 2015.
- [8] J. Choi and Y. Ko, "Compressive sensing based detector for sparse signal modulation in precoded OFDM," in *Proc. IEEE Intl. Conf. on Commun.*, Jun. 2015.
- [9] Y. Ko, "A tight upper bound on bit error rate of joint OFDM and multi-carrier index keying," *IEEE Commun. Lett.*, vol. 18, no. 10, pp. 1763–1766, Aug. 2014.
- [10] S. M. Kay, *Fundamentals of statistical signal processing: volume II detection theory*. Prentice Hall, 1998.
- [11] I. S. Gradshteyn and I. M. Ryzhik, *Table of Integrals, Series, and Products*. Academic Press:San Diego, CA, 6th Ed., 2000.